The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Winn Scandinavia is under license. Other trademarks and trade names are those of their respective owners.

ARCSOUND

Arcsound is a trademark by Winn Scandinavia AB

Winn Scandinavia AB I Idrottsvägen 37, 70232 Örebro, Sweden
www.winnscandinavia.com

Winn Scandinavia AB reserves for possible typos, factual or numeric errors that may have been printed on any material or other included accessories.

PC/MAC CONNECTION


USB-C lossless audio quality
Experience high-resolution, lossless audio by connecting your NOVA L speaker to your laptop or other compatible devices using the USB-C cable.

1. Use the USB-C cable to connect your device and the NOVA L speaker.
2. Press and hold the power button to turn NOVA L on.

   (To disconnect Bluetooth, press and hold the play/pause button).
3. Open the settings on your device, select the speaker, and enable it for audio output.

AURACAST™

To get an enhanced audio experience, connect several NOVA L speakers together with the Auracast™ function. You can connect up to 100 NOVA L speakers together! Power on the speakers and short press the **Auracast™ button (⁂)** on each speaker to connect them. Choose one of the speakers to connect to via Bluetooth, this speaker will work as the main speaker.



AURACAST™

Note:

A) When Auracast™ connection is successful, the main speaker will have a blue light and a white light glowing, and the secondary speakers will have a white light glowing.

B) To disconnect a speaker from Auracast™ mode, short press the **Auracast™ button (⁂)** on the speaker. If you press the button on the assigned main speaker, it can disconnect all the speakers in the Auracast™ connection.

C) When you have turned off the NOVA L speakers, the connection via Auracast™ needs to be remade as shown in the manual.

BATTERY INFO

When the speaker´s battery is low, it will issue a voice prompt, and the volume will automatically decrease. Charge the speaker with the included USB-C power cable.

LED INDICATION

Status	LED indication
Working mode	Blue light glowing
Pairing mode	Blue light blinking
Charging	Red light glowing
Fully charged	Red light stop glowing
Auracast™ paired main	White and Blue lights glowing
Auracast™ paired second	White light glowing
Auracast™ disconnected	White light stop glowing*
Bass boost mode	Green light glowing

*The white light may display differently according to the user's operation

SPECIFICATIONS

Product model	NOVA L
Drivers	Woofer: 53x93mm - 1pc Tweeter: 1" (25mm) - 1pc
Bass enhancers	Passive Radiators (80mm) - 2pcs
Bluetooth version (chip)	V5.4
Output	50W (35W + 15W)
Frequency response	60Hz - 20kHz
S/N (signal to noise ratio)	85dB
Battery type	Li-ion battery 7.2V 4500mAh 32.4Wh
Battery charging time	Approximately 4 hours
Playing time	Up to 30 hours*
Cabel type	USB-C charging cable

* Dependent on volume and audio content

SPECIFICATIONS

Cabel length	1m
Bluetooth profile	A2DP 1.4, AVRCP 1.6.2
BT transmitter freq. range	2402 MHz - 2480 MHz
BT transmitter power	+9dBm(EIRP)
BT transmitter modulation	GFSK, π/4 DQPSK, 8DPSK
Features	BT / Auracast™ / XBASS / Support DAC function /
Waterproof	IPX6
Product size (WxHxD)	90x245x90mm
Net weight	864g
Packaging size (WxHxD)	93x276x93mm
Gross weight	980g
Operation temperature	MAX 45°C

USER MANUAL

NOVA L

ARCSOUND

ARCSOUND

Thank you for purchasing an Arcsound product!
To ensure the best experience, please take a moment to read through this product manual carefully before use. Pay close attention to all warnings and follow the instructions provided. Keep the manual in a safe and easily accessible location for future reference.



SAFETY INFORMATION

For your safety and to ensure optimal performance, please observe the following precautions:

Battery Lifespan Protection:
To maintain the battery's health, ensure that you fully charge the NOVA L at least once every 3 months. Keep in mind that battery life may vary based on usage patterns and environmental factors.

IPX6 Rating – Waterproof and Dustproof:
The NOVA L is rated IPX6 for water and dust resistance, meaning it can withstand 100 liters of water sprayed onto it for 3 minutes at a pressure of 100 kPa.

Liquid Exposure Warning:
Never expose the NOVA L to liquids while it's connected to a cable. Additionally, avoid getting the speaker wet while charging, as this could result in permanent damage to both the speaker and its power source.

SAFETY INFORMATION

Impact of Chemicals and Saltwater:
Exposure to chemicals and salt from pool or ocean water can weaken the waterproof seals and damage the connector surface over time. Always rinse the NOVA L with fresh water after exposure to these elements to prevent damage.

Charging After Liquid Exposure:
If the NOVA L has been exposed to liquid, allow it to dry completely and ensure it is clean before charging. Charging while the speaker is wet could cause irreversible damage.

External Adapter Compatibility:
When using an external adapter, ensure that the output voltage and current do not exceed 5V/3A to avoid damaging the speaker.



WHAT'S INCLUDED



Bluetooth speaker




Quick start manual



USB-C charging cable


CONTROLS



- The default volume is set to 30% when the speaker is turned on.
- To skip to the next or previous song, press and hold the + or - button.
- Press and hold the **Play/Pause** button to disconnect Bluetooth.
- The speaker will automatically power off if not used for +20 min.

BLUETOOTH FUNCTION

1. Hold the Button for 3 Seconds to Power On / Off
2. Choose **Bluetooth mode** by pressing the On / Off button
3. Open the Bluetooth settings on your mobile device and select **"NOVA L"**






XBASS


NOVA L features a built-in Xbass function. By pressing this button you increase the low end frequencies in the audio to add a bass boost. Release your music with a greater impact!

1. Short press the Button to activate the bass boost
2. Short press the Button again to remove the bass boost



PC/MAC CONNECTION

DAC function: Experience High-resolution lossless audio over USB-C connection*



* High-resolution lossless audio over USB-C connection requires compatible lossless audio content from supported apps/services.